



# DCN-CONCS Concentus Channel Selector



- ▶ **Low susceptibility to mobile phones**
- ▶ **Compact, attractive delegate unit**
- ▶ **Built-in, fold-away, flat-panel loudspeaker**
- ▶ **Five voting buttons**
- ▶ **Cable connections located underneath the unit**
- ▶ **External present and fraud contact**

The DCN-CONCS is similar to the DCN-CON Standard Delegate Unit, but includes a built-in language channel selector. This makes it suitable for conferences where more than one language is used and simultaneous interpretations are available. The channel selector includes up and down select keys and a 2-digit display with backlighting, enabling rapid selection of the required language channel. Channel selection is automatically limited to the number of language channels available. The flat-panel loudspeaker offers superior acoustics with minimal feedback, thus increasing intelligibility. When the unit is not being used, the loudspeaker panel conveniently folds down.

## Functions

### Controls and Indicators

- Channel selector with channel number display with back lighting and channel select keys (up/down)
- Headphone volume control on each side of the unit
- Built-in fold-away flat-panel loudspeaker, automatically muted if a microphone is on
- Microphone 'on/off' or 'request-to-speak' button
- 'Microphone-on' indicator at the top of the loudspeaker
- Tri-color indicator above the microphone button:
  - Red microphone on indicator
  - Green 'Request-to-speak' confirmation indicator
  - Yellow 'VIP' indicator. 'VIP' is lit when the delegate unit is part of the notebook, which is only available when PC control software is used

- Five voting buttons with yellow LED confirmation indicators These can be used to register:
  - PRESENT, YES (+), NO (-), ABSTAIN (X), (parliamentary voting)
  - Numerals: 1 to 5 (multiple choice or opinion polls)
  - Rating scale: - -, -, 0, +, ++ (audience response)

### Interconnections

- Socket for pluggable microphone
- 2 m (78.7 in) cable terminated in a molded six-pole circular connector
- Socket for external microphone or headset microphone
- Six-pole circular connector for loop-through connections
- Eight-pole modular jack connector for Intercom Handset LBB 3555/00 and external present and fraud contact e.g. a fingerprint reader
- Left and right 3.5 mm (0.14 in) stereo jack type headphones sockets
- Connection 3.5 mm (0.14 in) for external microphone or stereo jack type headset microphone

## Certifications and Approvals

Region	Certification
Europe	CE

## Technical Specifications

### Electrical

#### Headphone connection

Frequency response	30 Hz to 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm

#### Headset connection

Frequency response	30 Hz - 20 kHz
Load impedance	> 32 ohm
Output power	2 x 15 mW/32 ohm

Nominal microphone input level 7 mVrms

Overload microphone input level > 124 mVrms

### Interface data

#### Recommended external microphone type (or headset microphone)

Element	Electret-condenser
Polar pattern	Omni directional
Operating voltage	5 VDC
Sensitivity	62 dB at 1200 ohm (0 dB = 1 V/mbar at 1 kHz)
Frequency response	100 Hz to 14 kHz
Connector	3.5 mm (0.14 in) jack mono or stereo

### Mechanical

Mounting Tabletop (portable or fixed mounting) and flush mounting

#### Dimensions (H x W x D) **(without microphone)**

Tabletop	50 x 275 x 155 mm 2.0 x 10.8 x 6.1 in)
Flush mounted	30 x 275 x 155 mm (1.2 x 10.8 x 6.1 in)

Weight 1.4 kg (3.1 lb)

Color top Charcoal (PH 10736) with silver (RAL 9022) panel

Color base Charcoal (PH 10736)

## Ordering Information

### DCN-CONCS Concentus Channel Selector

pluggable microphone, voting, channel select, 2 headphone sockets, microphone to be ordered separately

### Accessories

#### DCN-MICS Pluggable Short Microphone

length 310 mm (12.2 inch)

#### DCN-MICL Pluggable Long Microphone

length 480 mm (18.9 inch)

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: +31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Americas:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Bosch Security Systems Pte Ltd  
38C Jalan Pemimpin  
Singapore 577180  
Phone: +65 6319 3450  
Fax: +65 6319 3499  
apr.securitysystems@bosch.com  
www.boschsecurity.com

### Represented by