

LR-400 Display Receiver

Listen®

www.ListenTech.com

Specify Part Number

LR-400-072
or LR-400-216

Listen's LR-400 Portable Receiver offers a unique Look&Listen™ Display – Easily verify channel selection, whether or not channel is locked, battery level, and RF signal strength using the LR-400's LCD. A great choice for venues that change channels frequently or maintain several wireless audio systems.



Benefits

- Exceptional audio quality! 80dB sound-to-noise ratio!
- LCD makes maintenance easy – No need to guess about the status of your batteries or which channel you are on.
- Flexibility – Available in 72 or 216MHz.
- 57 Channels – Compatible with most other assistive listening (ALS) products.
- 100 % Digital – Listen receivers are digitally-tuned so transmission won't drift; assurance that when you select a channel, it stays on channel!
- UP, DOWN and SEEK buttons behind mechanically locking door, thus discouraging end users from changing the channel selected.
- Built in SmartCharge™ won't allow batteries to overcharge! Charging circuitry is conveniently built into Listen's receivers; never worry about unplugging a transformer at a certain time.

User Applications

- ADA compliance
- language interpretation
- meeting rooms
- meeting monitoring
- auditory description
- fitness centers
- convention centers
- judges chambers
- training facilities
- houses of worship
- tours
- offices
- cinemas
- schools
- trade shows
- amphitheaters
- parks
- zoos
- and many more!



Don't miss a single sound.

Listen Technologies Corporation
8535 South 700 West, Suite A
Sandy, UT 84070-2515 USA
Phone: +1.801.233.8992 or 1.800.330.0891
Fax: +1.801.233.8995
Email: info@ListenTech.com

LR-400 Display Receiver

Listen[®]

www.ListenTech.com



LR-400 Features

1. Line-level earphone jack (3.5mm) accepts either mono or stereo headsets.
2. Multifunction LED indicates power on, if batteries are low, and charging status.
3. Easy on/off volume control.
4. Receiver antenna is built into the earphone cord, eliminating additional wires while maximizing receiver effectiveness.
5. Look&Listen™ LCD Display shows channel selection, channel lock and battery level.
6. Manually lockable battery compartment door.
7. Charging plug port.
8. Adjustable squelch in 20 steps mutes audio on loss of RF signal.
9. Digitally tuned with UP, DOWN, and SEEK buttons behind manually lockable door. Electronically lock on channel by holding the SEEK button down 5 seconds to prevent tampering.
10. Uses two AA batteries. Selectable to use either alkaline or Listen's advanced NiMH Rechargeable AA Batteries. SmartCharge™ incorporated into receiver makes sure each unit receives the most beneficial charge.
11. Contact points for Listen's drop in charging cases.
12. Exclusive belt clip "loop" prevents unit from slipping off belt or strap.
13. When enabled, SQ provides highest audio quality available in its product category. SQ can be disabled for compatibility with other assistive listening equipment.

Don't miss a single sound.

Listen Technologies Corporation
8535 South 700 West, Suite A
Sandy, UT 84070-2515 USA

Phone: +1.801.233.8992 or 1.800.330.0891
Fax: +1.801.233.8995
Email: info@ListenTech.com

LR-400 Display Receiver Accessories

Listen[®]

www.ListenTech.com

Earphones



Ear Speaker
LA-164



Single Ear Bud
LA-161



Dual Ear Bud
LA-162



Consumer Camcorder Cable
LA-265



Professional Camcorder Cable
LA-266



Stereo Headset
LA-165



Neckloop
LA-166



Sacrificial Cable
LA-275

Architectural Specifications

The FM receiver shall be capable of receiving on 57 wide and narrow band channels with a SNR of 80dB or greater. The receiver shall be capable of seeking channels. The device shall have an adjustable squelch. The device shall have an audio frequency response of 50Hz to 15KHz, ± 3 dB at 72MHz, or of 50Hz to 10kHz, ± 3 dB at 216MHz. The device will incorporate a stereo headset jack that allows the user to plug in either a mono or stereo headset and listen to the audio normally. The device shall incorporate an LCD display that indicates channel, battery level, low battery, battery charging, RF signal strength. The receiver shall incorporate automatic battery charging circuitry for recharging of NiMH batteries. The Listen LR-400 is specified.

Warranty

Listen Technologies Corporation (Listen) warrants its receiver (LR-400) to be free from defects in workmanship and material under normal use and conditions for the useful lifetime of the product from date of purchase. All other products and accessories are warranted for ninety days from date of purchase. This warranty is only available to the original end purchaser of the product and cannot be transferred. Warranty is only valid if warranty card has been returned within 90 days of purchase. This warranty is void if damage occurred because of misuse or if the product has been repaired or modified by anyone other than a factory authorized service technician. Warranty does not cover normal wear and tear on the product or any other physical damage unless the damage was the result of a manufacturing defect. Listen is not liable for consequential damages due to any failure of equipment to perform as intended. Listen shall bear no responsibility or obligation with respect to the manner of use of any equipment sold by it. Listen specifically disclaims and negates any warranty of merchantability or fitness of use of such equipment including, without limitation, any warranty that the use of such equipment for any purpose will comply with applicable laws and regulations. Listen will only accept returned products with prepaid shipping and with a return authorization number. To receive a return authorization number call 1.800.330.0891 or +1.801.233.8992. Please see www.ListenTech.com or contact Listen for warranty details.

Don't miss a single sound.

Listen Technologies Corporation
8535 South 700 West, Suite A
Sandy, UT 84070-2515 USA

Phone: +1.801.233.8992 or 1.800.330.0891
Fax: +1.801.233.8995
Email: info@ListenTech.com

LR-400 Display Receiver



www.ListenTech.com

Specification		LR-400-072	LR-400-216
RF	RF Frequency Range	72.025 - 75.950 MHz	216.025 - 216.975 MHz
	Number of Channels	57 (17 wide, 40 narrow)	57 (19 wide, 38 narrow)
	Sensitivity	.6uV typical, 1 uV maximum for 12dB SINAD	
	Frequency Accuracy	± .005% stability 0° to 50°C (32° to 122° F)	
	Antenna	Uses earphone cable	
	Antenna Connector	3.5mm connector	
	Squelch	Programmable in 20 steps	
Compliance	FCC Part 15, Industry Canada		
Audio	** All system specifications are wireless end-to-end		
	System Frequency Response	63Hz - 15kHz (±3dB)	63Hz - 10kHz (±3dB)
	System Signal to Noise Ratio (A-weighted)	SQ enabled: 80dB; SQ disabled 60dB	SQ enabled: 80dB; SQ disabled 50dB
	System Distortion	<2% total harmonic distortion (THD) at 80% deviation	
	Output	3.5mm connectors, unbalanced, 0dBu nominal output level, 16mW maximum, impedance 32 Ohms	
Controls	Set Up Controls	Alkaline/NiMH batteries and SQ enable/disable and programmable squelch setting.	
	User Controls	Volume, channel UP/DOWN, SEEK (All controls except volume are electronically lockable, and are behind the door)	
	Programming	Squelch can be adjusted for sensitivity and signal capture control. Channel selection can be locked by holding the SEEK button for 5 seconds. Unit cannot be programmed to seek only used channels, however, it is capable of entering squelch mode.	
Indicators	LCD Display	Indicates channel, RF signal strength, lock status, and squelch setting.	
	LED	Red, illuminates when unit is on. Flashes when batteries are low. Flashes when charging. Flashes when locked and user attempts to seek to another channel.	
Power	Battery Type	Two AA batteries, alkaline or NiMH	
	Battery Life (Listen batteries)	30 hours alkaline (LA-361), 15 hours NiMH rechargeable (LA-362)	
	Battery Charging (NiMH only)	Fully automatic, 14 hours	
	Power Supply Connector	2.3mm OD by 0.7mm ID, barrel type connector. 7.5VDC, center positive <250mA. Drop in contact points for use with Listen charging/carrying cases.	
	Compliance	UL Listed	
Physical	Dimensions	3.0 in x 1.0 in x 5 in WxDxH (7.6cm x 2.5cm x 13.cm)	
	Unit Weight	3.9oz (111g)	
	Unit Weight with batteries	5.8 oz (164.4g)	
	Shipping Weight	1.0 lbs (453.6kg)	
	Door	Manually lockable. UP, DOWN and SEEK protected by door.	
Environmental	Temperature - Operation	-10° to 40°C (14° to 104° F)	
	Temperature - Storage	-20° to 50°C (-4° to 122° F)	
	Humidity	0 to 95% relative humidity, non-condensing	

Photographs, CAD drawings, etc. available at www.ListenTech.com.

Don't miss a single sound.

Listen Technologies Corporation Phone: +1.801.233.8992 or 1.800.330.0891
8535 South 700 West, Suite A Fax: +1.801.233.8995
Sandy, UT 84070-2515 USA Email: info@ListenTech.com